



Digital Velocity Decoder

D-VD-4N

Ultrafast FPGA-based Digital Signal Processing

Optomet Vibrometers feature an end-to-end FPGA-based digital signal processing allowing a fully digital read-out of the measurement data. Digital signal processing avoids any drawbacks of analog demodulation which may result from component aging, temperature dependencies, noise and non-linearities. Significantly higher sensitivity, better resolution, and stability are the benefits of OptoMET's end-to-end digital signal processing. Extremely low noise levels produce precise results even from poorly reflecting measurement objects.



HIGHLIGHTS:

- Digital decoder
- 9 velocity measuring ranges
- Frequency range: 0 Hz - 10 MHz
- Max. velocity up to 12 m/s
- Resolution down to 12 nm s⁻¹/Hz
- Max. linearity error: 0.5 %

High Frequency Velocity Decoder

All vibrometers series feature by default a velocity decoder and can be supplemented with a suitable displacement and/or acceleration decoder.

The D-VD-4N HF velocity decoder is the optimum solution for high-frequency processes up to 10 MHz. This fast digital decoder can measure vibration velocities between 12 nm/s and 12 m/s. It combines a large range of measuring frequencies with an excellent resolution. It is predestined for applications in microsystems engineering.

Technical data

Pos.	Full Scale Output (Peak) m/s	Typical Resolution* $\mu\text{m s}^{-1} / \sqrt{\text{Hz}}$	Signal Frequency Range kHz	Max. Acceleration g
1	0.0245	0.012	25	392
2	0.049	0.018	50	1,560
3	0.1225	0.024	100	7,800
4	0.245	0.05	250	39,200
5	0.49	0.10	500	156,000
6	1.225	0.20	1,000	784,000
7	2.45	0.29	1,500	2,350,000
8	4.9	0.47	2,500	7,840,000
9	12	2.40	10,000	76,800,000

* The resolution is defined as the signal amplitude (rms) that produces 0 dB signal/noise ratio with 1 Hz spectral resolution at 50 % f_{max} .

