



Digital Acceleration Decoder D-AD-4

Ultrafast FPGA-based Digital Signal Processing

Optomet Vibrometers feature an end-to-end FPGA-based digital signal processing allowing a fully digital read-out of the measurement data. Digital signal processing avoids any drawbacks of analog demodulation which may result from component aging, temperature dependencies, noise and non-linearities. Significantly higher sensitivity, better resolution, and stability are the benefits of OptoMET's end-to-end digital signal processing. Extremely low noise levels produce precise results even from poorly reflecting measurement objects.



HIGHLIGHTS:

- Digital decoder
- 9 acceleration measuring ranges
- Frequency range: 0 Hz - 10 MHz
- Max. acceleration 32,000,000 g
- Best acceleration resolution
70 $\mu\text{g} / \sqrt{\text{Hz}}$ *

High Frequency Acceleration Decoder

All vibrometers series feature by default a velocity decoder and can be supplemented with a suitable displacement and/or acceleration decoder.

The D-AD-4 acceleration decoder enables acceleration measurements up to 32 Mio. g at a maximum of 10 MHz and 5 m/s.
Required velocity decoder: D-VD-4

* The resolution is defined as the signal amplitude (rms) that produces 0 dB signal/noise ratio with 1 Hz spectral resolution at 50 % fmax.

Technical data

Pos.	Full Scale Output (Peak) g	Max. Frequency kHz	Max. Velocity m/s
1	160	25	5
2	640	50	5
3	3,200	100	5
4	16,000	250	5
5	64,000	500	5
6	320,000	1,000	5
7	960,000	1,500	5
8	3,200,000	2,500	5
9	32,000,000	10,000	5