



Digital Acceleration Decoder D-AD-5N

Ultrafast FPGA-based Digital Signal Processing

Optomet Vibrometers feature an end-to-end FPGA-based digital signal processing allowing a fully digital read-out of the measurement data. Digital signal processing avoids any drawbacks of analog demodulation which may result from component aging, temperature dependencies, noise and non-linearities. Significantly higher sensitivity, better resolution, and stability are the benefits of OptoMET's end-to-end digital signal processing. Extremely low noise levels produce precise results even from poorly reflecting measurement objects.



HIGHLIGHTS:

- Digital Decoder
- 14 acceleration measuring ranges
- Max. frequency up to 10 MHz
- Max. acceleration 78,400,000 g
- Best acceleration resolution 1.8 $\mu\text{g} / \sqrt{\text{Hz}}$ *

High-End Master Acceleration Decoder

All vibrometers series feature by default a velocity decoder and can be supplemented with a suitable displacement and/or acceleration decoder.

The D-AD-5N acceleration decoder was specially developed for use with velocity decoder D-VD-5N. It expands the laser Doppler vibrometers of the Vector Series with the capability of a real-time output of the acceleration value. Required velocity decoder: D-VD-5N

* The resolution is defined as the signal amplitude (rms) that produces 0 dB signal/noise ratio with 1 Hz spectral resolution at 50 % fmax.

Technical data

Pos.	Full Scale Output (Peak) g	Max. Frequency kHz	Max. Velocity m/s
1	3.9	2.5	25
2	15.6	5	25
3	78	10	25
4	392	25	25
5	1,560	50	25
6	7,800	100	25
7	39,200	250	25
8	156,000	500	25
9	784,000	1,000	25
10	2,350,000	1,500	25
11	7,840,000	2,500	25
12	78,400,000	10,000	25
13	62,700,000	5,000	25
14	40,000,000	2,500	25